

DATASHEET 5.0

8G-ZR-CXX-BR1

SFP+, 8/4/2 Gbps FC/FICON, CWDM, DDM, 23dB, 70km, 1470nm-1610nm (8ch)

OVERVIEW


The 8G-ZR-Cxx-BR1 is a versatile CWDM transceiver in SFP+ form-factor supporting a wide range of Fiber Channel (FC) services (2G to 8G). The transceiver has been layer-1 tested and approved by Brocade.

The transceiver is provided in 8 channel versions at the CWDM grid as specified in the ITU-T 694.2 standard.

The optical performance provides a bridgeable distance of up to 70km (without dispersion compensation) for 8G FC.

This transceiver provides digital diagnostic functions via a 2-wire serial interface as defined by the SFF-8472 specification.

The transceiver module is compliant to RoHS-6/6.



Safety/regulatory compliance:

RoHS	RoHS 6
Safety	EN 60825-1 Class 1 laser product
Storage Temp.	-40°C to 85°C

TECHNICAL DATA

PARAMETER	VALUE
Technology	CWDM SFP+
Transmission media	SM (2x LC)
Typical reach	70km
Nominal wavelengths	1470 - 1610 nm (8ch)
Bit rate range	2.125 – 8.5 Gbps
Protocol support	8G FC 4G FC 2G FC
Power budget	11 – 23dB
Dispersion tolerance	1400ps/nm ¹⁾
Dispersion penalty	Max 3dB
Temperature range	0°C to +70°C
Power consumption	< 1.6 W
Transmitter data:	
Output power	Min: -0.5 dBm Max: +4.0 dBm
Transmit wavelengths	1471 - 1611 nm in 20nm steps (G.694.2)
Receiver data:	
Minimum input power	-23.5 dBm ^{1) 2)}
Overload (max power)	-7.0 dBm
Wavelength range	1260 – 1620 nm
DDM	Yes
MSA compliance	SFF+ MSA

¹⁾ @ 14.025 Gbps (16G FC) ²⁾ @ BER < 1E-6 using PRBS 231-1 ³⁾ Average power

ORDERING INFORMATION

Part Number	Description
8G-ZR-C47-BR1	SFP+, 8/4/2 Gbps FC/FICON, CWDM 1470nm, DDM, 23dB, 70km
8G-ZR-C49-BR1	SFP+, 8/4/2 Gbps FC/FICON, CWDM 1490nm, DDM, 23dB, 70km
8G-ZR-C51-BR1	SFP+, 8/4/2 Gbps FC/FICON, CWDM 1510nm, DDM, 23dB, 70km
8G-ZR-C53-BR1	SFP+, 8/4/2 Gbps FC/FICON, CWDM 1530nm, DDM, 23dB, 70km
8G-ZR-C55-BR1	SFP+, 8/4/2 Gbps FC/FICON, CWDM 1550nm, DDM, 23dB, 70km
8G-ZR-C57-BR1	SFP+, 8/4/2 Gbps FC/FICON, CWDM 1570nm, DDM, 23dB, 70km
8G-ZR-C59-BR1	SFP+, 8/4/2 Gbps FC/FICON, CWDM 1590nm, DDM, 23dB, 70km
8G-ZR-C61-BR1	SFP+, 8/4/2 Gbps FC/FICON, CWDM 1610nm, DDM, 23dB, 70km

GENERAL DEFINITIONS

Technology	Grey; Transceiver type for non-WDM applications. Electrical or optical. CWDM; Transceiver type for CWDM applications using G.694.2 channel grid. DWDM; Transceiver type for DWDM applications using G.694.1 channel grid. BiDi; Transceiver pair using two different wavelength channels operating on a single-fiber. DAC: Direct Attach Cable. Electrical or optical cable with attached connectors.
Transmission Media	Type of fiber, e.g. Multimode (MM) or Singlemode (SM). Number of and connector type within brackets (e.g. 2x LC, 1x MPO).
Typical reach	Nominal distance performance based on dispersion and power budget properties, i.e. w/o dispersion compensation and optical amplification.
Bit rate range:	Supported bit rate range in Gigabit or Megabit per second (Gbps or Mbps).
Protocols:	Protocols within supported bit rate range.
Nominal wavelength	Typical wavelength from transmitter.
Interface standards	Referenced interface standards e.g. IEEE 802.3 standard for 10GbE services.
Power budget	Min and max power budget between Transmitter and Receiver. Excluding any dispersion penalty.
Dispersion tolerance/penalty	Maximum amount of tolerated dispersion and required reduction of power budget to maintain BER better than 1E-12. Defined at a specific bit rate.
Temperature range	Max operating case temperature range. Standard temperature range: Typically 0°C to +70°C (32°F to +158°F) Extended temperature range (E-temp): Typically -20°C to +75°C (-4°F to +167°F) Industrial temperature range (I-temp): -40°C to +85°C (-40°F to +185°F)
Power consumption	Worst case power consumption.
Transmitter Output power	Average output power. Provided in min and max values.
Receiver minimum input power	Minimum average input power at specified BER, normally 1E-12.
Receiver max input power	Maximum average input power giving a BER, normally 1E-12.
DDM	Digital Diagnostic Monitoring functionality as defined in SFF-8472 MSA.

Smartoptics makes no warranties or representations, expressed or implied, of any kind relative to the information or any portion thereof contained in this document or its adaptation or use, and assumes no responsibility or liability of any kind, including, but not limited to, indirect, special, consequential or incidental damages, for any errors or inaccuracies contained in the information or arising from the adaptation or use of the information or any portion thereof. The information in this document is subject to change without notice.